


Replacement Notes for : Alisun, 6-pin



Installations Notes:

One or two single Alisun 6-pin ballasts, pictured at left, are probably best replaced by the FA100 ballast using adapter harnesses 3-3IN-H for the input and 8-8OUT-H for the output as pictured below. This style of replacement may be the easiest to wire considering the poor original Alisun wiring connectors. If the FA100 is used to replace one Alisun ballast, simply leave the other output of the 8-8OUT-H harness unconnected. This will not harm the ballast. You will have to accommodate a difference in the footprint size of the ballasts. Check the FA100 data-sheet in this publication for actual measurements. Verify input voltage to the old ballast and move both input voltage selectors on the FA100 as required.

Typical Applications:

Alisun, Sunal

